



Control panel



3000 rpm Honda engine



17 It fuel tank



Stage V

We offer now what others will do tomorrow.



Genset s.p.a.

Via Stazione 5 - 27030 Villanova d'Ardenghi (PV) - Italy Phone:+39-0382-509 I

commerciale@genset.it www.genset.it



GenSet Next Gen technology for top business.

MH 6200 H/SA / TECHNICAL DATA

VEHICULAR GENERATOR - OUTPUT POWER 6,2 kVA SINGLE-PHASE 3000 RPM PETROL ENGINE SUPER-SILENCED VERSION WITH FUEL TANK AND MUFFLER INSIDE

Standard Features

- Remote control panel with:
 - Multifunction display showing single-phase generator voltage, battery voltage, frequency, hour meter, rpm
 - Start / Stop button
 - AUTO mode push-button for starting from external contact
- On board:
- Connection cable to remote panel
- · Safety shutdown in case of low oil level, high water temperature
- Circuit breaker for the generator protection.
- General shutdown switch
- Built-in muffler

Options available as factory options

- Fuel reserve indicator kit
- Fuel filler with key lock cap
- I mt tank connection pipe with fuel filler

Noise level

• Lwa 83 (58 dB a 7 mt)

AC generator - 50Hz

- Type: synchronous
- Single-phase power (max.): 6,2 kVA 230V
- Power Factor: cos φ 0,8

Petrol engine 3000 rpm

- Type: Honda GX 390 1 cyl. 11 hp (8,2 kWm) 390 cm³
- · Cooling system: air
- Starting system: electric
- Fuel tank capacity: 17 lt
- Fuel consumption @ 75%: 3,3 lt/h

Other features

- Insulation Class: H
- Ambient temperature: 40 °C (*)
- Altitude: 1000 mt (*)
- Mechanical Protection: IP 23
- Dimensions (L \times W \times H): 831 \times 513 \times 558 mm
- Dry weight: 150 kg