

# MG 7/5 I-BE



3000 rpm engine



Frontal panel



6,6 Lt Fuel tank



**Stage V**

We offer now what others will do tomorrow.



**Genset s.p.a.**

Via Stazione 5 - 27030  
Villanova d'Ardenghi (PV) - Italy  
Phone: +39-0382-5091

commerciale@genset.it  
www.genset.it

**GenSet**  
Next Gen technology  
for top business.

**PORTABLE SINGLE-PHASE POWER GENERATOR**  
**OUTPUT POWER 7,5 kVA THREE-PHASE AND 4 kVA SINGLE-PHASE**  
**PETROL ENGINE 3000 RPM**  
**6,6 LT FUEL TANK**

## Standard Features

- Low oil level shutdown device
- 1 x 16 A, 400 V - 50 Hz three-phase EEC socket
- 1 x 16 A, 230 V - 50 Hz single-phase EEC socket
- Protections for power outputs
- Earth Leakage Circuit Breaker (ELCB)

## Options

available as factory options

- Versions with different voltages
- 60Hz version
- Automatic voltage regulator (AVR)

## Accessories on request

- Trolley: two-wheels and handles

## Noise level

- Lwa 98 (73 dB a 7 mt)

## AC generator - 50Hz

- Type: synchronous
- Three-phase power (max.): 7,5 kVA - 400 V
- Single-phase power (max.): 4 kVA - 230 V
- Power Factor:  $\cos \phi$  0,8

## Petrol Engine 3000 rpm

- Type: Briggs & Stratton XR2100 - 1 cyl. - 11,9 HP (8,9 kWm) - 420 cm<sup>3</sup>
- Cooling system: air
- Starting system: recoil
- Fuel tank capacity: 6,6 lt
- Fuel consumption @ 75%: 3,6 lt/h

## Other features

- Insulation Class: H
- Ambient temperature: 40 °C (\*)
- Altitude: 1000 mt (\*)
- Mechanical Protection: IP 23
- Dimensions (L x W x H): 770 x 480 x 625 mm
- Dry weight: 84 kg

(\*) - For altitude and temperature values higher than those listed above, please consult the manufacturer to verify the available power.

In line with our continued development, innovation and voice of costumer program, we reserve the right to change data without notice.