



Control panel



5,5 Lt Fuel Tank



3000 rpm Yanmar Engine



We offer now what others will do tomorrow.



Gen Set s.p.a.

Via Stazione 5 - 27030 Villanova d'Ardenghi (PV) - Italy Phone:+39-0382-509 I

commerciale@genset.it www.genset.it



GenSet Next Gen technology for top business.

MG 6/4 I-D/AE-Y / TECHNICAL DATA

POWER GENERATOR
OUTPUT POWER 6,5 kVA THREE-PHASE AND 2,1 kVA SINGLE-PHASE
DIESEL ENGINE 3000 RPM
5,5 LT FUELTANK

Standard Features

- I x I6 A 230 V single-phase CEE socket
- I x I6 A 400 V three-phase CEE socket
- Starting battery
- Hourmeter
- Voltmeter
- · Low oil pressure and battery charger warning lights
- Power output protection
- Earth leakage circuit breaker
- Fitted for AMF-ATS or Remote control operation

Options available as factory options

- Versions with different voltages
- 60 Hz version
- Automatic voltage regulator (AVR)

Accessories on request

- AMF / ATS panel for auto start operation
- Trolley: two wheels and handles
- Remote control

Noise level

• Lwa 99 (74 dB a 7 mt)

AC generator - 50Hz

- Type: synchronous
- Three-phase power (max.): 6,5 kVA 400 V
- Single-phase power (max.): 2, I kVA 230 V
- Power Factor: cos φ 0,8

Diesel Engine 3000 rpm

- Type:Yanmar L100V 1 cyl. 8,8 HP (6,5 kWm) 435 cm³
- Cooling system: air
- Starting system: electric
- Fuel tank capacity: 5,5 lt
- Fuel consumption @ 75%: 1,5 lt/h

Other features

- Insulation Class: H
- Ambient temperature: 40 °C (*)
- Altitude: 1000 mt (*)
- Mechanical Protection: IP 23
- Dimensions (L \times W \times H): 820 \times 580 \times 610 mm
- Dry weight: 110 kg