

MG 6000 I-D/AE-Y



Control Panel



5,5 Lt Fuel Tank



3000 rpm
Yanmar Engine



Stage V

We offer now what others will do tomorrow.



GenSet s.p.a.

Via Stazione 5 - 27030
Villanova d'Ardenghi (PV) - Italy
Phone: +39-0382-5091

commerciale@genset.it
www.genset.it

 **GenSet**
Next Gen technology
for top business.

POWER GENERATOR
OUTPUT POWER 6,8 kVA SINGLE-PHASE
DIESEL ENGINE 3000 RPM
5,5 LT FUEL TANK

| | |
|--|---|
| <p>Standard Features</p> | <ul style="list-style-type: none"> • 1 x 16 A - 230V single-phase EEC socket • 1 x 32 A - 230V single-phase EEC socket • Starting battery • Hourmeter • Voltmeter • Low oil pressure and battery charger warning lights • Power output protection • Earth leakage circuit breaker • Fitted for AMF-ATS or Remote control operation |
| <p>Options available as factory options</p> | <ul style="list-style-type: none"> • Versions with different voltages • 60 Hz version • Automatic voltage regulator (AVR) |
| <p>Accessories on request</p> | <ul style="list-style-type: none"> • AMF / ATS panel for auto start operation • Trolley: two wheels and handles • Remote control |
| <p>Noise level</p> | <ul style="list-style-type: none"> • Lwa 99 (74 dB at 7 mt) |
| <p>AC generator - 50Hz</p> | <ul style="list-style-type: none"> • Type: synchronous • Single-phase power (max.): 6,8 kVA - 230 V • Power Factor: $\cos \phi$ 0,8 |
| <p>Diesel Engine 3000 rpm</p> | <ul style="list-style-type: none"> • Type: Yanmar L100V - 1 cyl. - 8,8 HP (6,5 kWm) - 435 cm³ • Cooling system: air • Starting system: electric • Fuel tank capacity: 5,5 lt • Fuel consumption @ 75%: 1,5 lt/h |
| <p>Other features</p> | <ul style="list-style-type: none"> • Insulation Class: H • Ambient temperature: 40 °C (*) • Altitude: 1000 mt (*) • Mechanical Protection: IP 23 • Dimensions (L x W x H): 820 x 580 x 610 mm • Dry weight: 110 kg |

(*) - For altitude and temperature values higher than those listed above, please consult the manufacturer to verify the available power.
In line with our continued development, innovation and voice of customer program, we reserve the right to change data without notice.